

supplementary

Honda CRF 250

1) Ignition coils

Disconnect BLACK wire from ignition coil. Connect YELLOW wire from QS wiring harness to ignition coil terminal. Connect BLACK wire (from motorcycle wiring harness) to RED wire from QS unit.
Connect BLUE wire from QS to YELLOW/BLUE wire on ignition coil.

2) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

