

supplementary Yamaha R1 1998-2001



1) Ignition coils

Disconnect R/B wire from each ignition coil. Connect yellow wire from QS wiring harness to ignition coil terminal. Connect R/B wires (from motorcycle wiring harness) to Red wires from QS unit. Connect Blue wire from QS to Orange (or Grey) on ignition coil.

2) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

