

# supplementary

## Honda CBR 600 1990-98

### 1) Ignition coils

Disconnect Black/White wire from ignition coil 1.

Connect Yellow wire from QS unit to ignition coil terminal and Red wire from QS unit to Black/White wire - see picture below.

Do it same with Black/White wire on ignition coil 2.

### 2) RPM connection

Connect Blue wire from QS unit to ignition coil #1-to Y/BI wire. Or to ignition coil #2-to BI/Y. Blue wire from QS have to be connected with Y/BI (or BI/Y) and ignition coil terminal.

### 3) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

### 4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

