

# supplementary

## Honda CBR 600 2001-2005



### 1) Ignition coils

Disconnect 6way balck connector on ignition coil wiring harness.  
Insert QS wiring harness - see picture below

Check if:

RED wire from QS goes to Black/White to motorcycle.

YELLOW wire from QS goes to Black/White to ignition coil.

### 2) Ground connection

Connect black wire of QS wiring harness to negative terminal of battery (or to frame of motorcycle)

### 3) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

