

supplementary

Suzuki GSX-R 1100 to year 1998



1) Ignition coils

Disconnect Orange/White wire from ignition coil 1.

Connect Yellow wire from QS unit to ignition coil terminal and Red wire from QS unit to Orange/White wire - see picture below.

Do it same with Black/Orange wire on ignition coil 2.

2) RPM connection

Connect Blue wire from QS unit to ignition coil #1-to W/B wire or to ignition coil #2-to black wire.

3) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

