

Supplementary Kawasaki ZX6R 2013



1) Ignition coils

Disconnect connectors from ignition coils and insert connectors of QS. Order is arbitrary. Check if White/Red wire of motorcycle wiring harness is connect with RED wire of QS wiring harness.

2) Gear position switch

Disconnect gear position connector - see picture below. Remove female pin-Green/Red wire from plastic body by needle. Insert female pin on Pink wires from QS ecu. Insert Gren/Red wire to plastic house on Pink wire.

3) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

